



email: office@byteart.at web: <u>www.byteart.at</u>

Installationsbeschreibung Bon-Drucker

Zu Beginn schließen Sie den Drucker an das Stromnetz und per USB an den Computer an. Schalten Sie den Drucker ein.

Die Installationsdatei können Sie unter <u>www.byteart.at</u> im Downloadbereich herunterladen. Starten Sie die Installation mit einem Doppelklick auf die heruntergeladene Datei *TMVirtualPortDriver830b.exe* auf Ihrem Computer.

1) Bestätigen Sie die Frage, ob Änderungen am Computer zugelassen werden sollen mit *Ja*. (Erscheint die Meldung nicht auf Ihrem Bildschirm, lassen Sie diesen Punkt aus.)

•	Benutzerkontensteuerung				
Möchten Sie zulassen, dass durch das folgende Programm Änderungen an diesem Computer vorgenommen werden?					
ā.	Programmname: Verifizierter Herausgebe Dateiursprung:	EPSON TM Virtual Port Driver Installer r: SEIKO EPSON CORPORATION Festplatte auf diesem Computer			
Details anzeigen		Ja Nein			
Anzeigezeitpunkt für die Benachrichtigungen ändern					

2) Bestätigen Sie die Sprachauswahl für Englisch mit OK. (Deutsch ist nicht verfügbar.)

EPSON	TM Virtual Port Driver Ver.8.30b - InstallShi			
Select the language for the installation from the choices below.				
	English (United States)			
	OK Cancel			

3) Klicken Sie im Assistenten auf die Schaltfläche Next>.

EPSON TM Virtual	Port Driver Ver.8.30b - InstallShield Wizard
	Welcome to the InstallShield Wizard for EPSON TM Virtual Port Driver Ver.8.30b The InstallShield Wizard will install EPSON TM Virtual Port Driver Ver.8.30b on your computer. To continue, click Next.
	< Back Next > Cancel

4) Bestätigen Sie die Lizenzvereinbarung, in dem Sie auf den Punkt links neben *I accept the terms of the license agreement.* und anschließend auf *Next>* klicken.

EPSON TM Virtual Port Driver Ver.8.30b - InstallShield Wizard	×			
License Agreement Please read the following license agreement carefully.	2			
SEIKO EPSON CORPORATION SOFTWARE LICENSE AGREEMENT IMPORTANT! READ THIS SOFTWARE LICENSE AGREEMENT CAREFULLY. The computer software product, fontware, typefaces and/or data, including any accompanying explanatory written materials (the "Software") should only be installed or used by the Licensee ("you") on the condition you agree with SEIKO EPSON CORPORATION ("EPSON") to the terms and conditions set forth in this Agreement. By installing or using the Software, you are representing to agree all the terms and conditions set forth in this Agreement. You should read this Agreement carefully before installing or using the Software. If you do not agree with the terms and conditions of this Agreement, you are not permitted to install or use the Software.	^			
I accept the terms of the license agreement I do not accept the terms of the license agreement InstallShield				

5) Wählen Sie Install.

EPSON TM Virtual Port Driver Ver.8.30b - InstallShield Wizard
Ready to Install the Program The wizard is ready to begin installation.
Click Install to begin the installation.
If you want to review or change any of your installation settings, click Back. Click Cancel to exit the wizard.
InstallShield

Warten Sie bis die Installation durchgeführt ist und das nächste Fenster erscheint.

6) Klicken Sie auf *Finish*.



7) Wählen Sie für den Drucker einen freien Port zwischen 3 und 9, zum Beispiel *COM5* und klicken Sie anschließend auf *Assign Port*.

	EPSON TM Virtual Po	ort Assignment Tool Ver.8.30	- 🗆 🗙
File Port Setting	View Help		
Port No.	Port Name	Port ID Assign Port	^
▲ Эсом1	Kommunikationsanschluss (COM1)		
\Lambda 🖳 сома	Kommunikationsanschluss (COM2)	🖉 Serial 1	
COM3		1 -	
COM4			
COM5			
COM6			
COM7			
COM8			
COM9			
COM10			
COM11			
COM12			
COM13			
COM14			
COM15			
COM16			
COM17			
COM18			
COM19			
COM20			
COM21			
COM22			
COM23			U
COM24			· · · ·
Test Print	Assign Port	Delete Port	Exit

8) Wählen Sie den vorgeschlagenen Port ID und danach OK.

COM5				
Assign port	Signal line Setting	Customer display port Setting Command	• •	
USB	Etherne	et COM/LPT		
A dev	vice is assigned by	associating this port to its USB serial number.		
Port	t ID	USB Serial Number		
A	TM-T20II	544338590791090000		
Othef	irst recognized dev	vice is automatically assigned to this port.		
۰) TM printer port			
) Customer display	port		
		OK Cance	I	

9) Klicken Sie auf *Exit*.

	EPSON TM Virtual Port As	signment Tool V	er.8.30 –	×
File Port Setting	J View Help			
Port No.	Port Name	Port ID	Assign Port	^
🔥 🖉 СОМ1	Kommunikationsanschluss (COM1)	🍠 Serial0		
🔥 🍠 сом2	Kommunikationsanschluss (COM2)	🍠 Serial 1		
COM3				
COM4		- Fin		
COM5	EPSON COM Emulation USB Port (COM5)		544338590791090000	
COMB				
COM8				
COM9				
COM10				
COM11				
COM12				
COM13				
COM14				
COM15				
COM16				
COM17 COM18				
COM18				
COM20				
COM21				
COM22				
COM23				
0M24				· ·
Test Print	Assign Port	Dele	te Port	Exit

Der Bon-Drucker ist jetzt einsatzbereit.